

Product datasheet

Specifications



Auxiliary contacts, TeSys Ultra,
2NO, 250VAC/DC, Power pole
status, screw terminal

LUFN20

Main

Range	TeSys
Device Short Name	LUFN
Product Or Component Type	Auxiliary contact

Complementary

Auxiliary Contact Composition	2 NO
[Ue] Rated Operational Voltage	<= 250 V AC <= 250 V DC
[Ui] Rated Insulation Voltage	250 V conforming to CSA 250 V conforming to IEC 60947-5-1 250 V conforming to UL
[Ith] Conventional Free Air Thermal Current	5 A
Minimum Switching Voltage	17 V
Minimum Switching Current	5 mA
Net Weight	0.05 kg

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	9.5 cm
Package 1 Width	3.3 cm
Package 1 Length	4.8 cm
Package 1 Weight	47.0 g
Unit Type Of Package 2	S02
Number Of Units In Package 2	60
Package 2 Height	15.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	3.162 kg

Contractual warranty

Warranty	18 months
----------	-----------

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Sustainability





Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)

Well-being performance

	Reach Free Of Svhc	
	Toxic Heavy Metal Free	
	Mercury Free	
	Rohs Exemption Information	Yes
Reach Regulation	REACH Declaration	
Eu Rohs Directive	Compliant EU RoHS Declaration	
China Rohs Regulation	China RoHS declaration	
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins	