# **Product data sheet**

Specifications





# TeSys Deca reversing contactor - 3P(3 NO) - AC-3 - <= 440 V 50 A - 230 V AC coil

LC2D50A3P7

! Discontinued on: Jul 12, 2021

#### (!) Discontinued

### Main

Range	TeSys
Product Name	TeSys Deca
Product Or Component Type	Reversing contactor
Device Short Name	LC2D
Contactor Application	Resistive load Motor control
Utilisation Category	AC-3 AC-1
Device Presentation	Preassembled with reversing power busbar
Poles Description	3P
Power Pole Contact Composition	3 NO
[Ue] Rated Operational Voltage	Power circuit <= 690 V AC 25400 Hz Power circuit <= 300 V DC
[le] Rated Operational Current	50 A (at <140 °F (60 °C)) at <= 440 V AC AC-3 for power circuit 80 A (at <140 °F (60 °C)) at <= 440 V AC AC-1 for power circuit
Motor Power Kw	15 kW at 220230 V AC 50 Hz 22 kW at 380400 V AC 50 Hz 30 kW at 500 V AC 50 Hz 33 kW at 660690 V AC 50 Hz 25 kW at 415 V AC 50 Hz 30 kW at 440 V AC 50 Hz
Motor Power Hp (UI / Csa)	3 hp at 115 V AC 60 Hz for 1 phase motors 7.5 hp at 230/240 V AC 60 Hz for 1 phase motors 15 hp at 200/208 V AC 60 Hz for 3 phase motors 15 hp at 230/240 V AC 60 Hz for 3 phase motors 40 hp at 460/480 V AC 60 Hz for 3 phase motors 40 hp at 575/600 V AC 60 Hz for 3 phase motors
Control Circuit Type	AC 50/60 Hz
[Uc] Control Circuit Voltage	230 V AC 50/60 Hz
Auxiliary Contact Composition	1 NO + 1 NC
[Uimp] Rated Impulse Withstand Voltage	6 kV IEC 60947
Overvoltage Category	III
[Ith] Conventional Free Air Thermal Current	10 A (at 140 °F (60 °C)) for signalling circuit 80 A (at 140 °F (60 °C)) for power circuit
Irms Rated Making Capacity	140 A AC for signalling circuit conforming to IEC 60947-5-1 250 A DC for signalling circuit conforming to IEC 60947-5-1 900 A at 440 V for power circuit conforming to IEC 60947
Rated Breaking Capacity	900 A at 440 V for power circuit conforming to IEC 60947

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



100 A gG at <= 899 V coordination type 2 for power circuit 100 A gG at <= 899 V coordination type 2 for power circuit 100 A gG at <= 899 V coordination type 2 for power circuit 1.5 mOhm - Ith 80 A 50 Hz for power circuit 1.5 mohm - Ith 80 A 50 Hz for power circuit 1.5 mohm - Ith 80 A 50 Hz for power circuit town connectors 1 0.00 0.0 in (1 35 mm) flexible 1.5 mohm - Ith 80 A 50 Hz for power circuit town circuit For Link BTR screw connectors 1 0.00 0.0 in (1 35 mm) flexible 1.5 mohm - Ith 80 A 50 Hz for power circuit town circuit For Link BTR screw connectors 2 0.00 0.0 in (1 35 mm) flexible 1.5 mohm - Ith 80 A 50 Hz for power circuit town circuit For Link BTR screw connectors 2 0.00 0.0 in (1 35 mm) flexible 1.5 mohm - Ith 80 A 50 Hz for power circuit town circuit For Link BTR screw connectors 2 0.00 0.0 in (1 35 mm) flexible 1.5 mohm - Ith 80 A 50 Hz for power circuit town circuit For Link BTR scr	
S4 A 14 T- (44 °C) - 10 min for power crount 208 A 10 15 °C (0°C) - 1 min for power crount 208 A 10 15 °C (0°C) - 1 min for power crount 100 A - 1 5 for signalling circuit 120 A - 10 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A gG at <= 690 V coordination type 1 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit 140 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 141 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 142 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 143 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 144 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 145 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 145 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 145 A gG at <= 690 V coordination type 2 for power circuit to 0 V CSA 145 A gG at <= 690 V coordination type 2 for power circuit to 0	
208 A 104 °F (40 °C) - 1 min for power circuit 100 A − 1 so for signalling circuit 120 A - 500 ms for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 100 A 9G at = 690 v Coordination type 1 for power circuit 100 A 9G at = 690 v Coordination type 1 for power circuit 100 A 9G at = 690 v Coordination type 2 for power circuit 100 A 9G at = 690 v Coordination type 2 for power circuit 100 A 9G at = 690 v Coordination type 2 for power circuit 100 A 9G at = 690 v Coordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 100 A 9G at = 690 v Locordination type 2 for power circuit 500 v LIC 60947-4-1 100 A 9G at = 600 v LIC 60947-4-1 100 A 9G at = 600 v LIC 60947-4-1 100 A 9G at = 600 v LIC 60947-4-1 100 A 9G at = 600 v LIC 60947-4-1 100 A 9G at = 600 v LIC 60947-4-1 100 A 9G at = 600 v LIC 600 v LIC 60947-4-1 100 A 9G at = 600 v LIC 600	
100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 150 A 9G at <= 690 V coordination type 1 for power circuit 150 A 9G at <= 690 V coordination type 2 for power circuit 150 A 9G at <= 690 V coordination type 2 for power circuit 150 A 9G at <= 690 V ECC 69947-4-1 Power circuit 600 V SA Signalling cir	84 A 104 °F (40 °C) - 10 min for power circuit
120 A - 500 ms for signalling circuit	208 A 104 °F (40 °C) - 1 min for power circuit
Associated Fuse Rating  10 A gG for signalling circuit conforming to IEC 60947-5-1 100 A gG at <= 690 V coordination type 1 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit  Werage Impedance  1.5 mOhm - Ith 80 A 50 Hz for power circuit 100 A gG at <= 690 V IEC 60947-4-1 Power circuit 600 V CSA Power circuit 600 V CSA Power circuit 600 V CSA Signalling circuit 6	100 A - 1 s for signalling circuit
Associated Fuse Rating  10 A gG for signalling circuit conforming to IEC 60947-5-1 100 A gG at <= 690 V coordination type 1 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit  Average Impedance  1.5 mOhm - Ith 80 A 50 Hz for power circuit  Power circuit 600 V CSA  Power circuit 600 V CSA  Power circuit 600 V CSA  Signalling circuit 600 V CSA  Signalling circuit 600 V UL  A Signalling circuit 600 V UL  Signalling circuit	120 A - 500 ms for signalling circuit
100 A gG at <= 690 V coordination type 2 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit 1.5 mOhm - Ith 80 A 50 Hz for power circuit  Power circuit 600 V CSA Power circuit 600 V CSA Power circuit 600 V LIC 60947-4-1 Power circuit 600 V LIC 60947-1 Signalling circuit 600 V LIC 60947-1 Signalli	140 A - 100 ms for signalling circuit
100 A gG at <= 690 V coordination type 2 for power circuit 100 A gG at <= 690 V coordination type 2 for power circuit 1.5 mOhm - Ith 80 A 50 Hz for power circuit 2.5 mohm - Ith 80 A 50 Hz for power circuit 2.5 mohm - Ith 80 A 50 Hz for power circuit EverLink BTR screw connectors 2.0.004 in 1(125 mm) fliexible 2.5 mohm - Ith 80 A 50 Hz for power circuit EverLink BTR screw connectors 2.0.004 in 1(125 mm) fliexible 2.5 mohm - Ith 80 A 50 Hz for power circuit EverLink BTR screw connectors 2.0.004 in 1(125 mm) fliexible 2.5 mohm - Ith 80 A 50 Hz for power circuit EverLink BTR screw connectors 2.0.004 in 1(125 mm) fliexible 2.5 mohm - Ith 80 A 50 Hz for power circuit EverLink BTR screw connectors 2.0.004 in 1(125 mm) fliexible 2.5 mohm - Ith 80 A 50 Hz for power circuit EverLink BTR screw connectors 2.0.004 in 1(125 mm) fliexible 2.5 mohm - Ith 80 A 50 Hz for power circuit EverLink	10 A aG for signalling circuit conforming to IEC 60947-5-1
Average Impedance  1.5 mOhm - Ith 80 A 50 Hz for power circuit  1.	
Power circuit 690 V IEC 60947-4-1 Power drout 600 V IEC 60947-4-1 Power drout 600 V IEC 60947-1 Signalling circuit 600 V	• • • • • • • • • • • • • • • • • • • •
Power circuit 800 V UL   Signalling circuit 600 V Sign	1.5 mOhm - Ith 80 A 50 Hz for power circuit
Power circuit 600 V UL   Signalling circuit 600 V IEC 60947-1   Signalling circuit 600 V UL   Signalling circuit 600 V UL   1.45 Mcycles 50 A AC-1 <= 440 V     1.1 Mcycles 80 A AC-1	Power circuit 690 V IEC 60947-4-1
Signalling circuit 690 V IEC 60947-1 Signalling circuit 600 V UL  1.45 Mcycles 50 A AC-3 <= 440 V 1.1 Mcycles 50 A AC-3 <= 440 V 1.1 Mcycles 50 A AC-1 <= 440 V 1.1 Mcycles 50 AC-1 <= 440 V 1.1 Mcycles 50 A AC-1 <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mcycles 50 AC-1  <= 440 V 1.1 Mc	Power circuit 600 V CSA
Signalling circuit 600 V CSA Signalling circuit 600 V UL  1.45 Mcycles 50 A AC-3 <= 440 V 1.1 Mcycles 80 A AC-1 <= 440 V 1.1 Mcycles 80 A AC-1 <= 440 V  Power Dissipation Per Pole 3.7 W AC-3 9.6 W AC-1  Front Cover With Interlocking Type Mechanical  Mounting Support Rail Plate  Standards CSA C22.2 No 14 EN 60947-8-1 EIC 60947-8-1 IEC 60947-8-1 ILC 60947-8-1 UL 508  Product Certifications GOST CCC CSA UL  Connections - Terminals Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2535 mm²)	Power circuit 600 V UL
Signalling circuit 600 V CSA Signalling circuit 600 V UL  1.45 Mcycles 50 A AC-3 <= 440 V 1.1 Mcycles 80 A AC-1 <= 440 V 2.1 Mcycles 80 A AC-1 <= 440 V 3.7 W AC-3 9.6 W AC-1  Front Cover  With  Mechanical  Mounting Support  Rail Plate  Standards  CSA C22.2 No 14 EN 60947-8-1 EIC 60947-8-1 EIC 60947-8-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²) flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²) flexible without cable end Power circuit EverLink BTR screw connectors 1 0.00 0.05 in² (125 mm²) flexible without cable end Power circuit EverLink BTR screw connectors 2 0.00 0.04 in² (125 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 1 0.00 0.05 in² (135 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 2 0.00 0.04 in² (125 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 2 0.00 0.04 in² (125 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 2 0.00 0.05 in² (135 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 2 0.00 0.04 in² (125 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 0.00 0.05 in² (135 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 0.00 0.05 in² (125 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 0.00 0.04 in² (125 mm²) flexible with cable end Power circuit EverLink BTR screw connectors 0.00 0.05 in² (2.535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.00 0.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.00 0.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.00 0.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.00 0.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm) Powe	Signalling circuit 690 V IEC 60947-1
Signalling circuit 600 V UL  1.45 Mcycles 50 A AC-3 <= 440 V 1.1 Mcycles 50 A AC-1 <= 440 V 1.1 Mcycles 80 A AC-1 < 1.5 Mcycles 80 A AC-1	· ·
1.1 Mcycles 80 A AC-1 <= 440 V  3.7 W AC-3 9.6 W AC-1  Front Cover  With  Mounting Support  Rail Plate  Standards  CSA C22.2 No 14 EN 60947-4-1 EN 60947-4-1 EIC 60947-4-1 EIC 60947-4-1 EIC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.05 in² (2535 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)	
1.1 Mcycles 80 A AC-1 <= 440 V  3.7 W AC-3 9.6 W AC-1  Front Cover  With  Mounting Support  Rail Plate  Standards  CSA C22.2 No 14 EN 60947-4-1 EN 60947-4-1 EIC 60947-4-1 EIC 60947-4-1 EIC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.05 in² (2535 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Power circuit 42.2 Eliclin (6 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)	1.45 Mcvcles 50 A AC-3 <= 440 V
Power Dissipation Per Pole  3.7 W AC-3 9.6 W AC-1  Front Cover  With  Mechanical  Mounting Support  Rail Plate  Standards  CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 IUL 508  Product Certifications  GOST CCC GSA UL  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (225 mm²)solid Power circui	·
Pront Cover With Interlocking Type Mechanical Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-4-1 IEC 60947-5-1 UL 508 Product Certifications GOST CCC CSA UL  Connections - Terminals Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 0.000.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm) Power circuit EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Operating Time 419 ms opening 1226 ms closing B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	<u> </u>
Mechanical	
Mounting Support  Rail Plate  Standards  CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-4-1 IEC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid	9.0 W AC-1
Rail   Plate	With
Plate  CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-4-1 IEC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 4.4.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load EN/ISO 13849-1	Mechanical
Standards  CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 0.000.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.18 in (4 mm)  Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.18 in (4 mm)  Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 ms) hexagonal 0.18 in (4 mm)  Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 ms) hexagonal 0.18 in (4 mm)  Goperating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	Rail
EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 4.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	CSA C22.2 No 14
IEC 60947-4-1 IEC 60947-5-1 UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.5 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm)  Power circuit 4.4.25 lbrin (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	EN 60947-4-1
Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	EN 60947-5-1
Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
UL 508  Product Certifications  GOST CCC CSA UL  Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.5 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2.535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (235 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (235 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	GOST
Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
Connections - Terminals  Control circuit spring terminals 1 0.00 in² (2.5 mm²)flexible without cable end Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit T0.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load EN/ISO 13849-1	
Control circuit spring terminals 2 0.00 in² (2.5 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load EN/ISO 13849-1	Control circuit spring terminals 1.0.00 in² (2.5 mm²)flexible without cable end
Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load EN/ISO 13849-1	
without cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	
Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	,
without cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	,
with cable end Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1	
Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)flexible with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	
with cable end Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	
Power circuit EverLink BTR screw connectors 1 0.000.05 in² (135 mm²)solid Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	,
Power circuit EverLink BTR screw connectors 2 0.000.04 in² (125 mm²)solid  Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	
Tightening Torque  Power circuit 70.81 lbf.in (8 N.m) EverLink BTR screw connectors 0.040.05 in² (2535 mm²) hexagonal 0.16 in (4 mm) Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  B10d = Mcycles	
(2535 mm²) hexagonal 0.16 in (4 mm)  Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Operating Time  419 ms opening 1226 ms closing  Safety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1  B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	- Ower Great EverLink DTN Sciew Connectors 2 0.000.04 III (125 IIIIIT)SOII0
Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in² (2.525 mm²) hexagonal 0.16 in (4 mm)  Departing Time  419 ms opening 1226 ms closing  Bafety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Wechanical Durability  6 Mcycles	
(2.525 mm²) hexagonal 0.16 in (4 mm)  419 ms opening 1226 ms closing  Bafety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Wechanical Durability  6 Mcycles	, , ,
Departing Time  419 ms opening 1226 ms closing  Bafety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Wechanical Durability  6 Mcycles	Power circuit 44.25 lbf.in (5 N.m) EverLink BTR screw connectors 0.000.04 in <sup>2</sup>
1226 ms closing  Bafety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1  B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	(2.525 mm²) hexagonal 0.16 in (4 mm)
1226 ms closing  Bafety Reliability Level  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability  6 Mcycles	419 ms opening
B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability 6 Mcycles	
B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1  Mechanical Durability 6 Mcycles	· · ·
	1226 ms closing
Maximum Operating Rate 3600 cvc/b 140 °F (60 °C)	1226 ms closing  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1
	1226 ms closing  B10d = 1369863 cycles contactor with nominal load EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load EN/ISO 13849-1
Safety Reliability Level  Mechanical Durability	

## Complementary

Coil Technology Without built-in suppressor module

Control Circuit Voltage Limits	0.30.6 Uc -40158 °F (-4070 °C) drop-out AC 50/60 Hz 0.81.1 Uc -40140 °F (-4060 °C) operational AC 50 Hz 0.851.1 Uc -40140 °F (-4060 °C) operational AC 60 Hz 11.1 Uc 140158 °F (6070 °C) operational AC 50/60 Hz
Inrush Power In Va	140 VA 60 Hz cos phi 0.75 (at 68 °F (20 °C)) 160 VA 50 Hz cos phi 0.75 (at 68 °F (20 °C))
Hold-In Power Consumption In Va	13 VA 60 Hz cos phi 0.3 (at 68 °F (20 °C)) 15 VA 50 Hz cos phi 0.3 (at 68 °F (20 °C))
Heat Dissipation	45 W 50/60 Hz
Auxiliary Contacts Type	Mechanically linked 1 NO + 1 NC IEC 60947-5-1 Mirror contact 1 NC IEC 60947-4-1
Signalling Circuit Frequency	25400 Hz
Minimum Switching Current	5 mA for signalling circuit
Minimum Switching Voltage	17 V for signalling circuit
Non-Overlap Time	1.5 ms on de-energisation between NC and NO contact     1.5 ms on energisation between NC and NO contact
Insulation Resistance	> 10 MOhm for signalling circuit

## **Environment**

Ip Degree Of Protection	IP20 front face IEC 60529
Climatic Withstand	IACS E10 IEC 60947-1 Annex Q category D
Protective Treatment	TH IEC 60068-2-30
Pollution Degree	3
Ambient Air Temperature For Operation	-40140 °F (-4060 °C) 140158 °F (6070 °C) with derating
Ambient Air Temperature For Storage	-76176 °F (-6080 °C)
Operating Altitude	09842.52 ft (03000 m)
Fire Resistance	1562 °F (850 °C) IEC 60695-2-1
Flame Retardance	V1 conforming to UL 94
Mechanical Robustness	Vibrations contactor open2 Gn, 5300 Hz Vibrations contactor closed4 Gn, 5300 Hz Shocks contactor open10 Gn for 11 ms Shocks contactor closed15 Gn for 11 ms
Height	4.80 in (122 mm)
Width	4.69 in (119 mm)
Depth	4.72 in (120 mm)
Net Weight	4.14 lb(US) (1.88 kg)

## Ordering and shipping details

Category	22357-CTR,TESYS D,OPEN,40-65A AC	
Discount Schedule	112	
Gtin	3389118340084	
Returnability	No	
Country Of Origin	FR	

# **Packing Units**

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	5.51 in (14 cm)
Package 1 Width	6.38 in (16.2 cm)
Package 1 Length	7.80 in (19.8 cm)
Package 1 Weight	4.63 lb(US) (2.1 kg)

## **Contractual warranty**

Warranty 18 months



**Green Premium**<sup>TM</sup> **label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >





Transparency RoHS/REACh

#### Well-being performance

<b>②</b>	Reach Free Of Svhc	
<b>⊘</b>	Toxic Heavy Metal Free	
<b>⊘</b>	Mercury Free	
<b>⊘</b>	Rohs Exemption Information Yes	
<b>Ø</b>	Pvc Free	

#### **Certifications & Standards**

Eu Rohs Directive	Compliant
	EU RoHS Declaration
China Rohs Regulation	China RoHS declaration  Pro-active China RoHS declaration (out of China RoHS legal scope)
Environmental Disclosure	Product Environmental Profile
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.
Circularity Profile	End of Life Information
California Proposition 65	WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to www.P65Warnings.ca.gov