Product data sheet

Specifications



auxiliary switch AX, EasyPact EZC100, EasyPact CVS 100BS, 1 common point changeover contact

EZAUX10

Main

Range Of Product	EZC100
Range	EasyPact
Device Short Name	AX
Product Or Component Type	Switch
Device Application	Signalling
Range Compatibility	EasyPact EZC circuit breaker
Signal Contacts Composition	1 NO/NC

Complementary

Auxiliary Contacts Type	Standard
[Ith] Conventional Free Air Thermal Current	5 A
[le] Rated Operational Current	AC-12: 3 A at 250 V AC 50/60 Hz
	AC-12: 5 A at 125 V AC 50/60 Hz
	AC-12: 5 A at 24 V AC 50/60 Hz
	AC-12: 5 A at 48 V AC 50/60 Hz
	AC-15: 2 A at 250 V AC 50/60 Hz
	AC-15: 3 A at 125 V AC 50/60 Hz
	AC-15: 5 A at 24 V AC 50/60 Hz
	AC-15: 5 A at 48 V AC 50/60 Hz
	DC-12: 0.2 A at 250 V DC
	DC-12: 0.4 A at 125 V DC
	DC-12: 2.5 A at 48 V DC
	DC-12: 4 A at 24 V DC
	DC-14: 0.2 A at 250 V DC
	DC-14: 0.4 A at 125 V DC
	DC-14: 1 A at 48 V DC
	DC-14: 3 A at 24 V DC
Minimum Load	10 mA at 24 V
Auxiliary Connection Terminal	Lead wire

Packing Units

-	
Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	2.5 cm
Package 1 Width	7.0 cm
Package 1 Length	8.5 cm
Package 1 Weight	40.0 g

Contractual warranty

Warranty

18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

Well-being performance

Reach Free Of Svhc	
V Toxic Heavy Metal Free	
Mercury Free	
Rohs Exemption Information	Yes
Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant EU RoHS Declaration
China Rohs Regulation	China RoHS declaration
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins