

TeSys D reversing contactor - 3P(3 NO) - AC-3 - <= 440 V 38 A - 100 V AC coil

LC2D38K7V

① Discontinued

Main

Mani	
Range	TeSys
Product Name	TeSys D
Product Or Component Type	Reversing contactor
Device Short Name	LC2D
Contactor Application	Resistive load Motor control
Utilisation Category	AC-1 AC-3
Device Presentation	Preassembled with reversing power busbar
Poles Description	3P
Power Pole Contact Composition	3 NO
[Ue] Rated Operational Voltage	Power circuit: <= 690 V AC 25400 Hz Power circuit: <= 300 V DC
[le] Rated Operational Current	50 A (at <60 °C) at <= 440 V AC AC-1 for power circuit 38 A (at <60 °C) at <= 440 V AC AC-3 for power circuit
Motor Power Kw	9 kW at 220230 V AC 50 Hz 18.5 kW at 380400 V AC 50 Hz 18.5 kW at 415440 V AC 50 Hz 18.5 kW at 500 V AC 50 Hz 18.5 kW at 660690 V AC 50 Hz
Motor Power Hp (UI / Csa)	10 hp at 230/240 V AC 60 Hz for 3 phases motors 5 hp at 240 V AC 60 Hz for 1 phase motors 10 hp at 200/208 V AC 60 Hz for 3 phases motors 20 hp at 480 V AC 60 Hz for 3 phases motors 25 hp at 600 V AC 60 Hz for 3 phases motors
Control Circuit Type	AC at 50/60 Hz
[Uc] Control Circuit Voltage	100 V AC 50/60 Hz
Auxiliary Contact Composition	1 NO + 1 NC
[Uimp] Rated Impulse Withstand Voltage	6 kV conforming to IEC 60947
Overvoltage Category	III
[lth] Conventional Free Air Thermal Current	10 A (at 60 °C) for signalling circuit 50 A (at 60 °C) for power circuit
Irms Rated Making Capacity	140 A AC for signalling circuit conforming to IEC 60947-5-1 250 A DC for signalling circuit conforming to IEC 60947-5-1 550 A at 440 V for power circuit conforming to IEC 60947
Rated Breaking Capacity	550 A at 440 V for power circuit conforming to IEC 60947

· · · · · · · · · · · · · · · · · · ·		
150 A 0 °C - 1 min for power circuit 301 A 0 °C - 1 min for power circuit 100 A - 1 s for signalling circuit 100 A - 1 s for signalling circuit 120 A - 50 ms for signalling circuit 140 A - 100 ms for signalling circuit 153 A gG at <= 690 V coordination type 1 for power circuit 153 A gG at <= 690 V coordination type 1 for power circuit 153 A gG at <= 690 V coordination type 2 for power circuit 150 V GS A get life of the signalling circuit signall	[Icw] Rated Short-Time Withstand	60 A 40 °C - 10 min for power circuit
310 A 0 °C - 10 s for power circuit 100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 120 A - 500 V conforming to IEC 60947-4-1 120 Power circuit 500 V Conforming to IEC 60947-4-1 120 Power circuit 500 V Conforming to IEC 60947-1 120 Signalling circuit 600 V Conforming to IEC 60947-1 120 Signalling c	Current	430 A 40 °C - 1 s for power circuit
100 A - 15 for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 153 A g6 at <= 690 V coordination type 1 for power circuit 653 A g6 at <= 690 V coordination type 2 for power circuit 653 A g6 at <= 690 V coordination type 2 for power circuit 653 A g6 at <= 690 V coordination type 2 for power circuit 653 A g6 at <= 690 V coordination type 2 for power circuit 653 A g6 at <= 690 V coordination type 2 for power circuit 653 A g6 at <= 690 V coordination type 2 for power circuit 653 A g6 at <= 690 V coordination type 2 for power circuit 654 A g6 at <= 690 V coordination type 2 for power circuit 655 A g6 at <= 690 V coordination type 2 for power circuit 657 A g6 at <= 690 V coordination type 2 for power circuit 658 A g6 at <= 690 V coordination type 2 for g6 at		150 A 40 °C - 1 min for power circuit
120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 130 A gG for signalling circuit conforming to IEC 60947-5-1 63 A gG at <= 690 V coordination type 2 for power circuit 63 A gG at <= 690 V coordination type 2 for power circuit 140 A - 100 ms for signalling circuit conforming to IEC 60947-4-1 Power circuit 500 V CSA certified Power circuit 500 V CSA certified Signalling circuit 680 V conforming to IEC 60947-4-1 Power circuit 500 V CSA certified Signalling circuit 690 V CSA certified Signalling circuit 690 V CSA certified Signalling circuit 600 V CSA certified Signalling cir		·
Associated Fuse Rating 10 A gG for signalling circuit conforming to IEC 60947-5-1 38 A gG at <= 690 V coordination type 1 for power circuit 27 MOhm - Ith 50 A 50 Hz for power circuit 28 A gG at <= 690 V coordination type 2 for power circuit 28 A gG at <= 690 V coordination type 2 for power circuit 28 Power circuit: 600 V CSA certified Power Coordination Power Pow		· · ·
Associated Fuse Rating 10 A gG for signalling circuit conforming to IEC 60947-5-1 83 A gG at <= 690 V coordination type 1 for power circuit 83 A gG at <= 690 V coordination type 1 for power circuit 83 A gG at <= 690 V coordination type 2 for power circuit 84 Average Impedance 2 m0hm - Ith 50 A 50 Hz for power circuit 850 W Les Cartified 850 W		· · ·
83 A gG at <= 690 V coordination type 1 for power circuit 83 A gG at <= 690 V condination type 2 for power circuit 83 A gG at <= 690 V condination type 2 for power circuit 84 Average Impedance 2 m0hm - 1h 50 A 50 Hz for power circuit 850 V Los Cartified Power circuit: 690 V CaS certified Signalling circuit: 690 V UL certified Signalling circuit: 690 V V UL certified Signalling circuit:		140 A - 100 ms for signalling circuit
Average Impedance 2 mOhm - Ith 50 A 50 Hz for power circuit (UI) Rated Insulation Voltage Power circuit: 600 V U. Cartified Signalling circuit: 600 V U. Carti	Associated Fuse Rating	
Average Impedance 2 mOhm - Ith 50 A 50 Hz for power circuit Power circuit: 689 V conforming to IEC 60947-4-1 Power circuit: 600 V LSA certified Signalling circuit:		
Power circuit: 690 V conforming to IEC 60947-4-1 Power circuit: 690 V CSA certified Signalling circuit: 690 V Conforming to IEC 60947-4-1 Power circuit: 690 V SA certified Signalling circuit: 690 V SA certified SA certified SA certified SA certified SA certified SA certified SA certified SA certified SA certified SA certified SA		63 A gG at <= 690 V coordination type 2 for power circuit
Power circuit: 800 V LC SA certified Power direct: 800 V LC sertified Signalling circuit: 800 V CSA certified Signalling circuit: 800 V LC certified 1.4 Mcycles 50 A AC-1 at Ue <= 440 V 1.4 Mcycles 38 A AC-3 at Ue <= 440 V 1.4 Mcycles 38 A AC-3 at Ue <= 440 V 1.4 Mcycles 38 A AC-3 at Ue <= 440 V 1.4 Mcycles 38 A AC-3 Front Cover With Interlocking Type Electrical and mechanical Mounting Support Plate Rail Standards CSA C22.2 No 14 EN 60947-8-1 EN 609	Average Impedance	2 mOhm - Ith 50 A 50 Hz for power circuit
Power circuit: 500 V LL certified Signalling circuit: 600 V conforming to IEC 60947-1 Signalling circuit: 600 V CSA certified	[Ui] Rated Insulation Voltage	· · · · · · · · · · · · · · · · · · ·
Signaling circuit: 600 V Conforming to IEC 60947-1		
Signalling circuit: 600 V CSA certified		
Signalling circuit: 600 V UL certified		
1.4 Mcycles 38 A AC-3 at Ue <= 440 V Power Dissipation Per Pole 5 W AC-1 3 W AC-3 Front Cover With Interlocking Type Electrical and mechanical Mounting Support Plate Rail Standards CSA C22.2 No 14 EN 60947-8-1 EIC 60947-8-1 EIC 60947-8-1 UL 508 Product Certifications LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 12 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 3 cable(s) 110 mm*flexible with cable end Power circuit: screw clam		
1.4 Mcycles 38 A AC-3 at Ue <= 440 V Power Dissipation Per Pole 5 W AC-1 3 W AC-3 Front Cover With Interlocking Type Electrical and mechanical Mounting Support Plate Rail Standards CSA C22.2 No 14 EN 60947-8-1 EC 60947-8-1 EC 60947-8-1 EC 60947-8-1 EC 60947-8-1 UL 508 Product Certifications LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 12 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 3 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 4 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 6 cable(s) 110 mm*flexible with cable end Powe	Electrical Durchility	4.4 Marrier 50.4 40.4 at the at 440.7
Front Cover With Interlocking Type Electrical and mechanical Mounting Support Plate Rail Standards CSA C22.2 No 14 EN 80947-5-1 IEC 80947-5 IEC 80947-1	Electrical Durability	•
Front Cover With Interlocking Type Electrical and mechanical Mounting Support Plate Rail Standards CSA C22.2 No 14 EN 80947-5-1 IEC 80947-5 IEC 80947-1	Payer Dissinction Per Pole	5,000
Front Cover Mith Interlocking Type Electrical and mechanical Mounting Support Plate Rail Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-4-1 EIC 60947-5-1 ILIC 6094	rowei Dissipation Per Pole	
Interlocking Type Electrical and mechanical Mounting Support Plate Rail Standards CSA C22.2 No 14 EN 60947-8-1 EIC 60947-8-1 IEC 60947-8-1 IEC 60947-8-1 IUL 508 LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 12 5 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 12 5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 with screwdriver Philips No 2 Power circuit: 2.5 N.m on screw clamp terminals - with sc		
Plate Rail	Front Cover	With
Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 UL 508 Product Certifications LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 15 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid	Interlocking Type	Electrical and mechanical
Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-4-1 IEC 60947-5-1 UL 508 LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 15 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid	Mounting Support	
EN 60947-4-1 EN 60947-5-1 IEC 60947-4-1 IEC 60947-5-1 UL 508 LROS (Lloyds register of shipping) CSA DNV CCC BY UL RINA GL GOST Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid		
EN 60947-5-1 IEC 60947-5-1 UL 508 LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 110 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circui	Standards	
IEC 60947-5-1 UL 508 LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Fightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 1222 ms closing 419 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
IEC 60947-5-1 UL 508 LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 15 mm²solid Control circuit: screw clamp terminals 1 cable(s) 15 mm²solid Control circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Deperating Time 1222 ms closing 419 ms opening Safety Reliability Level B10d = 1389863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load conforming to EN/ISO		
Product Certifications LROS (Lloyds register of shipping) CSA DNV CCC BV UL RINA GL GOST Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 15 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid		
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 n.m - on screw clamp t		
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit	Product Certifications	LROS (Lloyds register of shippina)
Connections - Terminals Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N		1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1
BV UL RINA GI GOST Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		DNV
UL RINA GL GOST Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		CCC
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 12 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 m.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp termi		
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 nm - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 nm - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 nm - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on s		
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver Philips No 2 **Departing Time** 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with sc	O	
Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	Connections - Terminals	
Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		. , ,
Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 1222 ms closing 419 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 1222 ms closing 419 ms opening Bafety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 1222 ms closing 419 ms opening Bafety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	Fightening Torque	Control circuit 1.7 N m - on corou clamp terminals with coroudding flat (2.5
Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 1222 ms closing 419 ms opening Bafety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	rigiteiling forque	•
Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 1222 ms closing 419 ms opening Bafety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
419 ms opening Bafety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		·
419 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	Operating Time	1222 ms closing
B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		•
	Safety Reliability Level	B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1
13849-1		
		13849-1
	Mechanical Durability	15 Mcycles
, io mojalo		

Maximum Operating Rate 3600 cyc/h 60 °C

Complementary

Coil Technology	Without built-in suppressor module
Control Circuit Voltage Limits	0.30.6 Uc (-4070 °C):drop-out AC 50/60 Hz 0.81.1 Uc (-4060 °C):operational AC 50 Hz 0.851.1 Uc (-4060 °C):operational AC 60 Hz 11.1 Uc (6070 °C):operational AC 50/60 Hz
Inrush Power In Va	70 VA 60 Hz cos phi 0.75 (at 20 °C) 70 VA 50 Hz cos phi 0.75 (at 20 °C)
Hold-In Power Consumption In Va	7.5 VA 60 Hz cos phi 0.3 (at 20 °C) 7 VA 50 Hz cos phi 0.3 (at 20 °C)
Heat Dissipation	23 W at 50/60 Hz
Auxiliary Contacts Type	type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1 type mirror contact 1 NC conforming to IEC 60947-4-1
Signalling Circuit Frequency	25400 Hz
Minimum Switching Current	5 mA for signalling circuit
Minimum Switching Voltage	17 V for signalling circuit
Non-Overlap Time	1.5 ms on de-energisation between NC and NO contact 1.5 ms on energisation between NC and NO contact
Insulation Resistance	> 10 MOhm for signalling circuit

Environment

Ip Degree Of Protection	IP20 front face conforming to IEC 60529
Protective Treatment	TH conforming to IEC 60068-2-30
Pollution Degree	3
Ambient Air Temperature For Operation	-4060 °C 6070 °C with derating
Ambient Air Temperature For Storage	-6080 °C
Operating Altitude	03000 m
Fire Resistance	850 °C conforming to IEC 60695-2-1
Flame Retardance	V1 conforming to UL 94
Mechanical Robustness	Vibrations contactor open: 2 Gn, 5300 Hz Vibrations contactor closed: 4 Gn, 5300 Hz Shocks contactor closed: 15 Gn for 11 ms Shocks contactor open: 8 Gn for 11 ms
Height	85 mm
Width	90 mm
Depth	92 mm
Net Weight	0.807 kg

Contractual warranty

Warranty 18 months