

Product datasheet

Specifications



ammeter dial Power Logic - 1.3 In - ratio 1250/5A

16085

⚠ Discontinued on: 28 May 2020

⚠ Discontinued

Main

Range Of Product	PowerLogic
Product Name	AMP
Product Or Component Type	Dial
Current Transformer Ratio	1250/5
Scale Type	80 mm over 90°
Mounting Support	Front face

Complementary

Type Of Measurement	Current
Scale	0-1250 A

Environment

Height	96 mm
Width	96 mm
Depth	75 mm

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	0.1 cm
Package 1 Width	8.6 cm
Package 1 Length	8.6 cm
Package 1 Weight	12.0 g
Unit Type Of Package 2	BB1
Number Of Units In Package 2	10
Package 2 Height	7.8 cm
Package 2 Width	15.0 cm
Package 2 Length	11.6 cm
Package 2 Weight	1.65 kg
Unit Type Of Package 3	S03
Number Of Units In Package 3	100

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 3 Height	30 cm
Package 3 Width	30 cm
Package 3 Length	40 cm
Package 3 Weight	16.987 kg

Contractual warranty

Warranty	18 months
----------	-----------

Sustainability




Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)

Well-being performance

	Reach Free Of Svhc	
	Mercury Free	
	Rohs Exemption Information	Yes
Reach Regulation		REACH Declaration
Eu Rohs Directive		Compliant with Exemptions
China Rohs Regulation		China RoHS declaration
Weee		The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins