

# variable speed drive ATV12 - 3kW - 200..240V - 3ph - with heat sink

ATV12HU30M3

! Discontinued on: Nov 1, 2020

#### ! Discontinued

#### Main

Range Of Product	Altivar 12
Product Or Component Type	Variable speed drive
Product Specific Application	Simple machine
Mounting Mode	Cabinet mount
Communication Port Protocol	Modbus
Supply Frequency	50/60 Hz +/- 5 %
[Us] Rated Supply Voltage	200240 V - 1510 %
Nominal Output Current	12.2 A
Motor Power Hp	4 hp
Motor Power Kw	3 kW
Motor Power Hp	4 hp
Emc Filter	Without EMC filter
Ip Degree Of Protection	IP20

## Complementary

Discrete Input Number	4
Discrete Output Number	2
Analogue Input Number	1
Analogue Output Number	1
Relay Output Number	1
Physical Interface	2-wire RS 485
Connector Type	1 RJ45
Continuous Output Current	12.2 A at 4 kHz
Method Of Access	Server Modbus serial
Speed Drive Output Frequency	0.5400 Hz
Speed Range	120
Sampling Duration	20 ms, tolerance +/- 1 ms for logic input 10 ms for analogue input
Linearity Error	+/- 0.3 % of maximum value for analogue input
Frequency Resolution	Analog input: converter A/D, 10 bits Display unit: 0.1 Hz

List Price displayed is VAT EXCLUSIVE.

Time Constant	
	20 ms +/- 1 ms for reference change
Transmission Rate	9.6 kbit/s
	19.2 kbit/s 38.4 kbit/s
Transmission Frame	RTU
Number Of Addresses	1247
Data Format	8 bits, configurable odd, even or no parity
Communication Service	Read holding registers (03) 29 words
	Write single register (06) 29 words
	Write multiple registers (16) 27 words Read/write multiple registers (23) 4/4 words
	Read device identification (43)
Type Of Polarization	No impedance
4 Quadrant Operation Possible	False
Asynchronous Motor Control Profile	Sensorless flux vector control
Profile	Quadratic voltage/frequency ratio Voltage/frequency ratio (V/f)
Maximum Output Frequency	4 kHz
Transient Overtorque	
	150170 % of nominal motor torque depending on drive rating and type of motor
Acceleration And Deceleration Ramps	Linear from 0 to 999.9 s S
	U
Motor Slip Compensation	Adjustable Preset in factory
Switching Frequency	216 kHz adjustable 416 kHz with derating factor
Nominal Switching Frequency	4 kHz
Nominal Switching Frequency  Braking To Standstill	4 kHz  By DC injection
Braking To Standstill	By DC injection
Braking To Standstill  Brake Chopper Integrated	By DC injection  False  19.0 A at 100 V (heavy duty)
Braking To Standstill  Brake Chopper Integrated  Line Current	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty)
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current  Network Frequency  Relative Symmetric Network	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)  5060 Hz
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current  Network Frequency  Relative Symmetric Network Frequency Tolerance	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)  5060 Hz
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current  Network Frequency  Relative Symmetric Network Frequency Tolerance  Prospective Line Isc  Base Load Current At High	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)  5060 Hz  5 %
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current  Network Frequency  Relative Symmetric Network Frequency Tolerance  Prospective Line Isc  Base Load Current At High Overload	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)  5060 Hz  5 %  5 kA
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current  Network Frequency  Relative Symmetric Network Frequency Tolerance  Prospective Line Isc  Base Load Current At High Overload  Power Dissipation In W  With Safety Function Safely	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)  5060 Hz  5 %  5 kA  12.2 A  Forced cooling: 94.0 W
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current  Network Frequency  Relative Symmetric Network Frequency Tolerance  Prospective Line Isc  Base Load Current At High Overload  Power Dissipation In W  With Safety Function Safely Limited Speed (SIs)  With Safety Function Safe Brake	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)  5060 Hz  5 %  5 kA  12.2 A  Forced cooling: 94.0 W  False
Braking To Standstill  Brake Chopper Integrated  Line Current  Maximum Input Current  Maximum Output Voltage  Apparent Power  Maximum Transient Current  Network Frequency  Relative Symmetric Network Frequency Tolerance  Prospective Line Isc  Base Load Current At High Overload  Power Dissipation In W  With Safety Function Safely Limited Speed (SIs)  With Safety Function Safe Brake Management (Sbc/Sbt)  With Safety Function Safe	By DC injection  False  19.0 A at 100 V (heavy duty) 15.9 A at 120 V (heavy duty)  15.9 A  240 V  6.6 kVA at 240 V (heavy duty)  18.3 A during 60 s (heavy duty) 20.1 A during 2 s (heavy duty)  5060 Hz  5 %  5 kA  12.2 A  Forced cooling: 94.0 W  False

With Safety Function Safe Speed Monitor (Ssm)	False
With Safety Function Safe Stop 1 (Ss1)	False
With Sft Fct Safe Stop 2 (Ss2)	False
With Safety Function Safe Torque Off (Sto)	False
With Safety Function Safely Limited Position (Slp)	False
With Safety Function Safe Direction (Sdi)	False
Protection Type	Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t
Tightening Torque	1.2 N.m
Insulation	Electrical between power and control
Quantity Per Set	Set of 1
Width	140 mm
Height	184 mm
Depth	141.2 mm

## **Environment**

Operating Altitude	<= 1000 m without derating > 10003000 m with current derating 1 % per 100 m
Operating Position	Vertical +/- 10 degree
Product Certifications	NOM CSA C-Tick UL GOST RCM KC
Marking	CE
Standards	UL 508C UL 618000-5-1 IEC 61800-5-1 IEC 61800-3
Assembly Style	With heat sink
Electromagnetic Compatibility	Electrical fast transient/burst immunity test level 4 conforming to IEC 61000-4-4 Electrostatic discharge immunity test level 3 conforming to IEC 61000-4-2 Immunity to conducted disturbances level 3 conforming to IEC 61000-4-6 Radiated radio-frequency electromagnetic field immunity test level 3 conforming to IEC 61000-4-3 Surge immunity test level 3 conforming to IEC 61000-4-5 Voltage dips and interruptions immunity test conforming to IEC 61000-4-11
Environmental Class (During Operation)	Class 3C3 according to IEC 60721-3-3 Class 3S2 according to IEC 60721-3-3
Maximum Acceleration Under Shock Impact (During Operation)	150 m/s² at 11 ms
Maximum Acceleration Under Vibrational Stress (During Operation)	10 m/s² at 13200 Hz
Maximum Deflection Under Vibratory Load (During Operation)	1.5 mm at 213 Hz
Volume Of Cooling Air	16.4 m3/h

Overvoltage Category	Class III
Regulation Loop	Adjustable PID regulator
Electromagnetic Emission	Radiated emissions environment 1 category C2 conforming to IEC 61800-3 216 kHz shielded motor cable Conducted emissions conforming to IEC 61800-3
Vibration Resistance	1 gn (f = 13200 Hz) conforming to IEC 60068-2-6 1.5 mm peak to peak (f = 313 Hz) - drive unmounted on symmetrical DIN rail - conforming to IEC 60068-2-6
Shock Resistance	15 gn conforming to IEC 60068-2-27 for 11 ms
Relative Humidity	595 % without condensation conforming to IEC 60068-2-3 595 % without dripping water conforming to IEC 60068-2-3
Noise Level	50 dB
Pollution Degree	2
Ambient Air Transport Temperature	-2570 °C
Ambient Air Temperature For Operation	-1050 °C without derating 5060 °C with current derating 2.2 % per °C
Ambient Air Temperature For Storage	-2570 °C

## **Packing Units**

•	
Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	22.000 cm
Package 1 Width	21.500 cm
Package 1 Length	22.000 cm
Package 1 Weight	2.436 kg
Unit Type Of Package 2	P06
Number Of Units In Package 2	12
Package 2 Height	75.000 cm
Package 2 Width	60.000 cm
Package 2 Length	80.000 cm
Package 2 Weight	42.232 kg

## **Contractual warranty**

Warranty 18 months

#### **Sustainability**

Weee

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

## Well-being performance

Mercury Free	
Rohs Exemption Information	Yes
Reach Regulation	REACh Declaration
Eu Rohs Directive	Pro-active compliance (Product out of EU RoHS legal scope)
China Rohs Regulation	China RoHS declaration

collection and never end up in rubbish bins


The product must be disposed on European Union markets following specific waste

## ATV12HU30M3


#### **Dimensions Drawings**

#### **Dimensions**

#### **Drive without EMC Conformity Kit**



#### **Drive with EMC Conformity Kit**




#### ATV12HU30M3


Mounting and Clearance

#### **Mounting Recommendations**


#### **Clearance for Vertical Mounting**



#### **Mounting Type A**




#### **Mounting Type B**



Remove the protective cover from the top of the drive.

#### **Mounting Type C**




Remove the protective cover from the top of the drive.

## ATV12HU30M3

#### Connections and Schema

#### **Three-Phase Power Supply Wiring Diagram**




A1 Drive

KM1 Contactor (only if a control circuit is needed)

Q1 Circuit breaker

## **Recommended Schemes**

#### 2-Wire Control for Logic I/O with Internal Power Supply




LI1: Forward

LI•: Reverse


A1: Drive

#### 3-Wire Control for Logic I/O with Internal Power Supply



LI1: Stop
LI2: Forward
LI•: Reverse
A1: Drive


#### Analog Input Configured for Voltage with Internal Power Supply



(1) 2.2 k $\Omega$ ...10 k $\Omega$  reference potentiometer

A1: Drive


#### **Analog Input Configured for Current with Internal Power Supply**



(2) 0-20 mA 4-20 mA supply

A1: Drive


#### Connected as Positive Logic (Source) with External 24 vdc Supply



(1) 24 vdc supply

A1: Drive

#### Connected as Negative Logic (Sink) with External 24 vdc supply



(1) 24 vdc supply


A1: Drive

## **Product data sheet**

#### ATV12HU30M3

#### Performance Curves

#### **Torque Curves**



- 1: Self-cooled motor: continuous useful torque (1)
- 2: Force-cooled motor: continuous useful torque
- 3: Transient overtorque for 60 s
- 4: Transient overtorque for 2 s
- 5: Torque in overspeed at constant power (2)
- (1) For power ratings  $\leq$  250 W, derating is 20% instead of 50% at very low frequencies.
- (2) The nominal motor frequency and the maximum output frequency can be adjusted from 0.5 to 400 Hz. The mechanical overspeed capability of the selected motor must be checked with the manufacturer.