



NEMA Motor Starter, Type S, replacement coil, 208VAC 60Hz, NEMA Size 00, 0 and 1 starters and 8903SM lighting

3104140048

Product availability: Stock - Normally stocked in distribution facility

Price*: 98.00 USD

Main

Product Or Component Type	Coil
Accessory / Separate Part Destination	Class 8502 type SA (series A)/SB/SC contactor Class 8536 type SA (series A)/SB/SC starter Class 8903 type SM lighting contactor

Complementary

Nema Size	0 00 1
[Ue] Rated Operational Voltage	208 V AC 60 Hz
Inrush Power In Va	245 VA
Average Consumption	27 VA
Height	2.15 in (54.7 mm)
Width	3.21 in (81.5 mm)
Depth	1.90 in (48.3 mm)

Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
Gtin	785901107378
Returnability	Yes
Country Of Origin	MX

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	2.10 in (5.334 cm)
Package 1 Width	2.80 in (7.112 cm)
Package 1 Length	3.30 in (8.382 cm)
Package 1 Weight	7.04 oz (199.581 g)

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Warranty

18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

Eu Rohs Directive

Not applicable, out of EU RoHS legal scope