# Product data sheet

Specifications

SQUARE D



# COMBO STARTER 600VAC 540A NEMA

8538SHW12V07

U To be discontinued on: Sep 30, 2024

① To be discontinued

Product availability: Non-Stock - Not normally stocked in distribution facility

#### Main

Product	Combination Starter
Туре	S
Control Circuit Type	Common control circuit

#### Complementary

Control Circuit Voltage	550 V AC 50 Hz 600 V AC 60 Hz
Starter Type	Non reversing
Number Of Poles	3P
Horsepower Rating	400 hp 460 V AC, 3 phase 400 hp 575 V AC, 3 phase
Maximum Voltage Rating	600 V AC
Control Units	No control units
Pilot Light	No indicator
Auxiliary Contacts	Without
Thermal Overload Type	Melting alloy 3
Disconnect Type	Fusible disconnect switch H, 600 A
Nema Size	6

#### Environment

Enclosure Type

NEMA 4 painted sheet steel with external reset

### Ordering and shipping details

Category	21218 - 8538,39 W/STAINLESS ENCLOS
Discount Schedule	CP1
Returnability	No
Country Of Origin	MX

#### **Packing Units**

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Weight	440.00 lb(US) (199.581 kg)

Price is "List Price" and may be subject to a trade discount - check with your local distributor or retailer for actual price.

## **Contractual warranty**

Warranty

18 months

#### **Sustainability**

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

**Eu Rohs Directive** 

Not compliant