

Product data sheet

Specifications

SQUARE D



LIGHTING CONTACTOR 600VAC 30A L

8903LA30V81C6C33F4T

! Discontinued

Main

| | |
|---------------------------|--------------------------------------|
| Product Or Component Type | Electrically Held Lighting Contactor |
| Range Of Product | 8903L |
| Control Circuit | Control circuit transformer |

Complementary

| | |
|-------------------------|--|
| Control Circuit Voltage | 120 V AC 60 Hz secondary circuit 480 V AC 60 Hz primary circuit |
| Current Rating | 20 A tungsten 30 A fluorescent |
| Number Of Poles | 3P 3 NO |
| Control Unit | Key-operated selector switch ON-OFF) |
| Pilot Light | No indicator |
| Control Circuit Fusing | 2 fuses primary circuit |
| Electrical Connection | Screw-clamp terminals |

Environment

| | |
|------------------------|-------------------------------------|
| Enclosure Type | NEMA 12 painted sheet steel surface |
| Product Certifications | UL Listed CSA |

Ordering and shipping details

| | |
|-------------------|-----------------------|
| Category | 21321-8903 L (NOT LX) |
| Discount Schedule | CP1 |
| Returnability | No |
| Country Of Origin | MX |

Contractual warranty

| | |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.