



Starter, Definite Purpose, nonreversing, 25A, 2 pole, 1 phase, 480VAC coil, melting alloy overload, NEMA 1, +options

8911DPSG23V06

Product availability: Stock - Normally stocked in distribution facility

Price*: 412.02 USD

Main

Product	Definite Purpose Starter	
Ampere Rating	25 A	
Horsepower Rating	2 hp 115 V AC, 1 phase 5 hp 230 V AC, 1 phase 10 hp 230 V AC, 3 phase 15 hp 460 V AC, 3 phase 20 hp 575 V AC, 3 phase	
Maximum Voltage Rating	600 V AC	
Control Circuit Voltage	440 V AC 50 Hz 480 V AC 60 Hz	
Phase	3 phase	

Complementary

Enclosure Material	Painted sheet steel	
Enclosure Rating	NEMA 1	
Locked Rotor Amperes	150 A 230 V AC	
	125 A 460 V AC	
	100 A 575 V AC	
Number Of Poles	3P	
Range	DPS	
Overload Type	Melting alloy	
Number Of Thermal Units	3	

Ordering and shipping details

Category	US10CP121381
Discount Schedule	0CP1
Gtin	785901024675
Returnability	Yes
Country Of Origin	MX

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package 1 Height	6.50 in (16.51 cm)
Package 1 Width	6.80 in (17.272 cm)
Package 1 Length	11.30 in (28.702 cm)
Package 1 Weight	5.80 lb(US) (2.631 kg)

Contractual warranty

Warranty 18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

Well-being performance

Mercury Free		
Rohs Exemption Information	Yes	
Reach Regulation	REACh Declaration	
Eu Rohs Directive	Compliant with Exemptions	
China Rohs Regulation	China RoHS declaration Product out of China RoHS scope. Substance declaration for your information.	