

Product data sheet

Specifications



coil LX1-LC - 415-440 V AC 50Hz,

LX1LC415

⚠ Discontinued on: Jul 12, 2021

⚠ Discontinued

Main

Range	TeSys
Device Short Name	LX1
Product Or Component Type	Coil
[Uc] Control Circuit Voltage	415...440 V AC 50 Hz
Power Consumption In Va	12...18 VA AC 0.3 60 Hz sealed 170...230 VA AC 0.55 60 Hz inrush
Value Of Inductance	0.107 mH closed circuit
Average Resistance	570.767 Ohm +/- 10 %

Complementary

Range Compatibility	TeSys LX1 contactor
Net Weight	0.26 lb(US) (0.12 kg)

Ordering and shipping details

Category	22384-STARTERS,INTEGRAL,ACCESS
Discount Schedule	I11
Gtin	3389110246384
Returnability	No
Country Of Origin	FR

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	2.76 in (7 cm)
Package 1 Width	1.97 in (5 cm)
Package 1 Length	3.15 in (8 cm)
Package 1 Weight	4.41 oz (125 g)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)

California Proposition 65

WARNING: Cancer - www.P65Warnings.ca.gov
