Specifications



LX1LD380

AC 50/60 Hz

() Discontinued on: Jan 23, 2021

TeSys Integral - coil - 380...400 V

① Discontinued

Main

Range	TeSys
Product Or Component Type	Coil
Range Compatibility	TeSys TeSys Integral contactor breaker
Device Short Name	LX1
Control Circuit Type	AC 50/60 Hz
[Uc] Control Circuit Voltage	380400 V AC 50 Hz 460480 V AC 60 Hz
Average Resistance	93.63 Ohm 68 °F (20 °C)
Inductance Of Closed Circuit	20 H

Complementary

Control Circuit Voltage Limits	Operational: 0.851.1 Uc (at <131 °F (55 °C)) Drop-out: 0.250.7 Uc (at <131 °F (55 °C))
Inrush Power In Va	420500 VA 60 Hz cos phi 0.55 350400 VA 50 Hz cos phi 0.55
Hold-In Power Consumption In Va	2436 VA 60 Hz cos phi 0.28 2030 VA 50 Hz cos phi 0.28

Environment

Net Weight

0.66 lb(US) (0.3 kg)

Ordering and shipping details

Category	22341-CONTACTOR,D,K,&F ACCESS
Discount Schedule	112
Gtin	3389110182361
Returnability	No
Country Of Origin	FR

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	3.15 in (8 cm)
Package 1 Width	2.95 in (7.5 cm)

Price is "List Price" and may be subject to a trade discount - check with your local distributor or retailer for actual price.

Package 1 Length

4.13 in (10.5 cm)

Package 1 Weight

0.68 lb(US) (0.31 kg)

Contractual warranty

Warranty

18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

California Proposition 65

WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide which is known to the State of California to cause Carcinogen harm. For more information go to www.p65warnings.ca.gov