

# Product data sheet

Specifications



## analog ammeter scale - 0..75 A

16007

### Main

Range Of Product	PowerLogic
Product Name	AMP
Product Or Component Type	Dial
Device Application	Motor
Current Transformer Ratio	75/5
Scale Type	62 mm over 90°
Mounting Support	Front face

### Complementary

Type Of Measurement	Current
Scale	0-75-225 A

### Environment

Height	72 mm
Width	72 mm
Depth	75 mm

### Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	0.1 cm
Package 1 Width	6.2 cm
Package 1 Length	8.0 cm
Package 1 Weight	8.0 g
Unit Type Of Package 2	BB1
Number Of Units In Package 2	10
Package 2 Height	8.7 cm
Package 2 Width	8.5 cm
Package 2 Length	8.7 cm
Package 2 Weight	117.0 g
Unit Type Of Package 3	S03
Number Of Units In Package 3	200

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 3 Height	30 cm
Package 3 Width	30 cm
Package 3 Length	40 cm
Package 3 Weight	2.827 kg

## Contractual warranty

Warranty	18 months
----------	-----------

## Sustainability

**Green Premium™ label** is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)

## Well-being performance

 Reach Free Of Svhc	
 Mercury Free	
 Rohs Exemption Information	Yes
Reach Regulation	<a href="#">REACH Declaration</a>
Eu Rohs Directive	Compliant with Exemptions
China Rohs Regulation	<a href="#">China RoHS declaration</a>
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins