# Product data sheet

Specifications



## Adapter terminal block, TeSys Deca, for separate mounting of LRD04L-D32L LR3D04L-D32L LR9D01-D32

LAD7B205

#### Main

Range	TeSys
Product Or Component Type	Terminal block
Device Short Name	LAD
Product Compatibility	LR9D LRDL LR3DL
Quantity Per Set	Set of 1
Accessory / Separate Part Category	Connection accessory

## Complementary

Connections - Terminals	Screw terminals	
Height	85 mm	
Width	45 mm	
Depth	87 mm	
Net Weight	0.12 kg	

## **Packing Units**

U	
Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	4.7 cm
Package 1 Width	8.2 cm
Package 1 Length	9.0 cm
Package 1 Weight	96.0 g
Unit Type Of Package 2	S02
Number Of Units In Package 2	20
Package 2 Height	15.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	2.262 kg

### **Contractual warranty**

Warranty

18 months

## **Sustainability**

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

### Well-being performance

Reach Free Of Svhc	
Toxic Heavy Metal Free	
Mercury Free	
Rohs Exemption Information	Yes
Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant EU RoHS Declaration
China Rohs Regulation	China RoHS declaration Pro-active China RoHS declaration (out of China RoHS legal scope)
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
California Proposition 65	WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to www.P65Warnings.ca.gov