

TeSys Deca contactor , 4P(4 NO) , AC-1 , <= 440V, 40 A , 96 V DC low cons coil

LC1DT40DL

! Discontinued

Main

Range	TeSys
Range Of Product	TeSys Deca
Product Or Component Type	Contactor
Device Short Name	LC1D
Contactor Application	Resistive load
Utilisation Category	AC-1 AC-3 AC-3e AC-4
Poles Description	4P
[Ue] Rated Operational Voltage	Power circuit: <= 690 V AC 25400 Hz Power circuit: <= 300 V DC
[le] Rated Operational Current	40 A (at <60 °C) at <= 440 V AC AC-1 for power circuit
[Uc] Control Circuit Voltage	96 V DC

Complementary

•	
Compatibility Code	LC1D
Pole Contact Composition	4 NO
Contact Compatibility	M5
Protective Cover	With
[Ith] Conventional Free Air Thermal Current	10 A (at 60 °C) for signalling circuit 40 A (at 60 °C) for power circuit
Irms Rated Making Capacity	140 A AC for signalling circuit conforming to IEC 60947-5-1 250 A DC for signalling circuit conforming to IEC 60947-5-1 450 A at 440 V for power circuit conforming to IEC 60947
Rated Breaking Capacity	450 A at 440 V for power circuit conforming to IEC 60947
[Icw] Rated Short-Time Withstand Current	50 A 40 °C - 10 min for power circuit 120 A 40 °C - 1 min for power circuit 240 A 40 °C - 10 s for power circuit 380 A 40 °C - 1 s for power circuit 100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit
Associated Fuse Rating	10 A gG for signalling circuit conforming to IEC 60947-5-1 63 A gG at <= 690 V coordination type 1 for power circuit 40 A gG at <= 690 V coordination type 2 for power circuit
Average Impedance	2 mOhm - Ith 40 A 50 Hz for power circuit
Power Dissipation Per Pole	3.2 W AC-1

[Ui] Rated Insulation Voltage	Power circuit: 600 V CSA certified Power circuit: 600 V UL certified Signalling circuit: 690 V conforming to IEC 60947-1 Signalling circuit: 600 V CSA certified Signalling circuit: 600 V UL certified Power circuit: 690 V conforming to IEC 60947-4-1
Overvoltage Category	III
Pollution Degree	3
[Uimp] Rated Impulse Withstand	6 kV conforming to IEC 60947
Voltage Safety Reliability Level	B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1
Mechanical Durability	30 Mcycles
Electrical Durability	1.4 Mcycles 40 A AC-1 at Ue <= 440 V
Control Circuit Type	DC low consumption
Coil Technology	Built-in bidirectional peak limiting diode suppressor
Control Circuit Voltage Limits	0.10.3 Uc (-4070 °C):drop-out DC 0.81.25 Uc (-4060 °C):operational DC 11.25 Uc (6070 °C):operational DC
Inrush Power In W	2.4 W (at 20 °C)
Hold-In Power Consumption In W	2.4 W at 20 °C
Operating Time	65.4588.55 ms closing 2030 ms opening
Time Constant	40 ms
Maximum Operating Rate	3600 cyc/h 60 °C
Connections - Terminals	Control circuit: screw clamp terminals 2 12.5 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible without cable end
	Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: flexible without cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible without cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end
Tightening Torque	cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible without cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 1 2.510 mm² - cable stiffness: solid without cable end
Tightening Torque Auxiliary Contact Composition	cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible without cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.510 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.516 mm² - cable stiffness: solid without cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips
	cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible without cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2
Auxiliary Contact Composition	cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible without cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 1 NO + 1 NC type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1
Auxiliary Contact Composition Auxiliary Contacts Type	cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible without cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.510 mm² - cable stiffness: solid without cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 1 NO + 1 NC type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1 type mirror contact 1 NC conforming to IEC 60947-4-1
Auxiliary Contact Composition Auxiliary Contacts Type Signalling Circuit Frequency	cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Control circuit: screw clamp terminals 2 14 mm² - cable stiffness: solid without cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible without cable end Power circuit: connector 2 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 1 2.510 mm² - cable stiffness: flexible with cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Power circuit: connector 2 2.516 mm² - cable stiffness: solid without cable end Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2 1 NO + 1 NC type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1 type mirror contact 1 NC conforming to IEC 60947-4-1

Non-Overlap Time	1.5 ms on de-energisation between NC and NO contact1.5 ms on energisation between NC and NO contact
Mounting Support	Plate Rail
Environment	
Standards	CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-4-1 IEC 60947-5-1 UL 508
Product Certifications	UL GL CCC RINA LROS (Lloyds register of shipping) GOST BV DNV CSA
Ip Degree Of Protection	IP20 front face conforming to IEC 60529
Protective Treatment	TH conforming to IEC 60068-2-30
Climatic Withstand	conforming to IACS E10 exposure to damp heat conforming to IEC 60947-1 Annex Q category D exposure to damp heat
Permissible Ambient Air Temperature Around The Device	-6080 °C storage -4060 °C operation 6070 °C with derating
Operating Altitude	03000 m
Fire Resistance	850 °C conforming to IEC 60695-2-1
Flame Retardance	V1 conforming to UL 94
Mechanical Robustness	Vibrations contactor open (2 Gn, 5300 Hz) Vibrations contactor closed (4 Gn, 5300 Hz) Shocks contactor closed (15 Gn for 11 ms) Shocks contactor open (8 Gn for 11 ms)
Height	91 mm
Width	45 mm
Depth	107 mm
Net Weight	0.425 kg

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1

Contractual warranty

Warranty	18 months
----------	-----------