Specifications



Changeover Contactor, TeSys Deca, 4P(4NO), AC-1, <=440V, 40A, 125 V DC coil, screw clamp terminals

LC2DT40GD

Main

IVIAIII	
Range	TeSys TeSys Deca
Product Name	TeSys Deca TeSys Deca
Product Or Component Type	Changeover contactor
Device Short Name	LC2D
Contactor Application	Resistive load
Utilisation Category	AC-1 AC-3 AC-3e AC-4
Device Presentation	Preassembled with reversing power busbar
Poles Description	4P
Power Pole Contact Composition	4 NO
[Ue] Rated Operational Voltage	Power circuit: <= 690 V AC 25400 Hz Power circuit: <= 300 V DC
[le] Rated Operational Current	40 A (at <60 °C) at <= 440 V AC AC-1 for power circuit
Control Circuit Type	DC standard
[Uc] Control Circuit Voltage	125 V DC
Auxiliary Contact Composition	1 NO + 1 NC
[Uimp] Rated Impulse Withstand Voltage	6 kV conforming to IEC 60947
Overvoltage Category	11
[Ith] Conventional Free Air Thermal Current	10 A (at 60 °C) for signalling circuit 40 A (at 60 °C) for power circuit
Irms Rated Making Capacity	140 A AC for signalling circuit conforming to IEC 60947-5-1 250 A DC for signalling circuit conforming to IEC 60947-5-1 450 A at 440 V for power circuit conforming to IEC 60947
Rated Breaking Capacity	450 A at 440 V for power circuit conforming to IEC 60947
[Icw] Rated Short-Time Withstand Current	50 A 40 °C - 10 min for power circuit 120 A 40 °C - 1 min for power circuit 240 A 40 °C - 10 s for power circuit 380 A 40 °C - 1 s for power circuit 100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit
Associated Fuse Rating	10 A gG for signalling circuit conforming to IEC 60947-5-1 63 A gG at <= 690 V coordination type 1 for power circuit 40 A gG at <= 690 V coordination type 2 for power circuit
Average Impedance	2 mOhm - Ith 40 A 50 Hz for power circuit

Power circuit: 800 V CSA certified Power circuit: 800 V Lordfred Signalling circuit: 600 V UL certified Signalling circuit: 600 V UL certified Electrical Durability 1.4 Mcycles 40 A AC-1 at Ue <= 440 V Power Dissipation Per Pole 3.2 W AC-1 Front Cover With Interlocking Type Mechanical Mounting Support Rail Plate Standards Standards CSA C22.2 No 14 EN 60947-8-1 EC 60947-4-1 EC 60947-8-1 EC 60947-8-1 EC 60947-8-1 EC 60947-8-1 EC 6035-1 EC 6035-1 Product Certifications UL CSA CC2 CCC EA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm*fle	
Signaling circuit: 600 V conforming to IEC 60947-1 Signaling circuit: 600 V UL certified Electrical Durability 1.4 Mcycles 40 A AC-1 at Ue <= 440 V Power Dissipation Per Pole 3.2 W AC-1 Front Cover With Interlocking Type Mechanical Mounting Support Rail Plate Standards Standards CSA C22.2 No 14 EN 60947-8-1 IEC 60947-8-1 IEC COLL Control circuit: serve damp terminals 1 cable(s) 14 mm ³ flexible without Cole rout control circuit: serve damp terminals 2 cable(s) 14 mm ³ flexible without Cole rout control circuit: serve damp terminals 2 cable(s) 14 mm ³ flexible without cole rout control circuit: serve damp terminals 2 cable(s) 14 mm ³ flexible without cole rout control circuit: serve damp terminals 1 cable(s) 14 mm ³ flexible without cole rout control circuit: serve damp terminals 1 cable(s) 14 mm ³ flexible without cole rout control circuit: serve damp terminals 1 cable(s) 14 mm ³ flexible without cole rout control circuit: serve damp terminals 1 cable(s) 14 mm ³	
Signaling circuit: 600 V CSA certified Signaling circuit: 600 V UL certified Electrical Durability 1.4 Mcycles 40 A AC-1 at Ue <= 440 V Power Dissipation Per Pole 3.2 W AC-1 Front Cover With Interlocking Type Mechanical Mounting Support Rail Plate Signaling of the second s	
Signalling circuit: 600 V UL certified Electrical Durability 1.4 Mcycles 40 A AC-1 at Ue <= 440 V Power Dissipation Per Pole 3.2 W AC-1 Front Cover With Interlocking Type Mechanical Mounting Support Rail Plate Plate Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-4-1 IEC 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 608 IEC 60335-1 Product Certifications UL CSA CC EU-RO-MR by DNV-GL Control circuit: screw clamp terminals 1 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible end Power cir	
Power Dissipation Per Pole 3.2 W AC-1 Front Cover With Interlocking Type Mechanical Mounting Support Rail Plate Plate Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-4-1 EN 60947-5-1 UL 508 EC 60335-1 Product Certifications UL SSA CCC EAC UKCA CC EAC UKCA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm ³ flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm ³ flexible without cable of Power circuit: connector 1 cable(s) 2.510 mm ³ flexible without cable of Power circuit: connector 1 cable(s) 2.510 mm ³ flexible without cable of Power circuit: connector 1 cable(s) 2.510 mm ³ flexible without cable of Power circuit: connector 1 cable(s) 2.510 mm ³ flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm ³ flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm ³ flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Q mm Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozi Con	
Front Cover With nterlocking Type Mechanical Wounting Support Rail Plate Standards CSA C22.2 No 14 EN 60947.4-1 IEC 60947.4-1 IEC 60947.4-1 IEC 60947.5-1 UL 508 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible with cut Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible with cut Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible with cut Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible with cut Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible with cut Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm?flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm?flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm?flexible with cable end Power circuit: 1.7 Nm - on screw clamp terminals - with screwdriver flat Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 Nm - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 Nm - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 Nm - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 Nm - on screw clamp terminals - wit	
Interlocking Type Mechanical Mounting Support Raii Plate Standards CSA C22.2 No 14 EN 60947-4-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 IEC 60947-5-1 UL 508 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without control circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Q Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on	
Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-4-1 IEC 60947-4-1 IEC 60947-4-1 IEC 60947-5-1 UL 508 IEC 60335-1 Product Certifications UL CSA CC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm*flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm*flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Over circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozi Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozi Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozi Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozi Control circuit: 1.7 N.m - on	
Plate Standards CSA C22.2 No 14 EN 60947-5-1 IEC 60947-4-1 EN 60947-5-1 UL 508 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*solid without cable control circuit: screw clamp terminals 2 cable(s) 14 mm*solid without cable end Power circuit: connector 1 cable(s) 2.5 10 mm*flexible with cable end Power circuit: connector 2 cable(s) 2.5 10 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.5 10 mm*flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozit Control circ	
Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.5 10 mm*flexible with cable end Power circuit: connector 2 cable(s) 2.5 10 mm*flexible with cable end Power circuit: connector 2 cable(s) 2.5 10 mm*flexible with cable end Power circuit: connector 2 cable(s) 2.5 10 mm*flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m	
EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 IEC 6035-1 Product Certifications UL SA CCC EAC UKCA CB EU-RO-MR by DNV-GL Control circuit: screw clamp terminals 1 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm?flexible without cable of Power circuit: connector 1 cable(s) 2.510 mm?flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm?flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm?flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Q Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Q Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid <td></td>	
EN 60947-5-1 IEC 60947-4-1 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm*flexible without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat C Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip No 2 Power circuit: 1.7 N.m - on screw clamp terminals - wit	
IEC 60947-5-1 UL 508 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with cable Control circuit: screw clamp terminals 2 cable(s) 14 mm*solid without control circuit: screw clamp terminals 2 cable(s) 14 mm*solid without cable ond Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: 1.7 Nm - on screw clamp terminals - with screwdriver flat Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver flat Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 Nm - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 Nm - on screw clamp terminals - with screwdriver pozid Control circu	
IEC 60947-5-1 UL 508 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on sc	
UL 508 IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cable control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cable control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat & Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver prizit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver prizit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver prizit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver prizit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver prizit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver prizit Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver prizit Control circuit: 1.7 N.m - on screw clamp terminals - wit	
IEC 60335-1 Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 1 cable(s) 14 mm³solid without cable control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cable of control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible with cable end Power circuit: connector 2 cable(s) 2.516 mm³solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozi	
Product Certifications UL CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without ca Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without cable control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible without cable end Power circuit: connector 1 cable(s) 2.516 mm*solid without cable end Power circuit: 1.C numetor 1 cable(s) 2.516 mm*solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Q Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Q Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver point Control circuit: 1.7 N.m - on sc	
CSA CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm³flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm³flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cab Power circuit: connector 1 cable(s) 2.510 mm³flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm³flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm³flexible without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw cla	
CCC EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Cont	
EAC UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm ² flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm ² flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm ² flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm ² flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm ² flexible without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm ² flexible without cab Power circuit: connector 1 cable(s) 2.510 mm ² flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm ² flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm ² flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm ² flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm ² flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm ² flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm ² flexible without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat & Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat & Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver poxid Control circuit: 1.7 N.m - on screw clamp termin	
UKCA CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible with out Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without ca Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without ca Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without ca Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid without ca Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm*flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm*flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Q Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m	
CB EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm³flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm³flexible with cab Control circuit: screw clamp terminals 1 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 1 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm³solid without cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control cir	
EU-RO-MR by DNV-GL Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without ca Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals	
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdri	
Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without ca Power circuit: connector 1 cable(s) 2.510 mm²flexible with cut cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat <i>Q</i> Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals	
Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with out Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without cat Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without cat Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals -	le without cable end
Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cath Control circuit: screw clamp terminals 2 cable(s) 125 mm²flexible with c Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid without can Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without can Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwd	
Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with c Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with sc	
Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid without ca Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without ca Power circuit: connector 1 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with	
Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid without ca Power circuit: connector 1 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with scr	
Power circuit: connector 1 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat @ Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with sc	
Power circuit: connector 2 cable(s) 2.510 mm²flexible without cable end Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 1 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat @ Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on connector - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdri	
Power circuit: connector 1 cable(s) 2.510 mm²flexible with cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: connector 1 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat @ Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on connector - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver	
Power circuit: connector 1 cable(s) 2.516 mm²solid without cable end Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Safety R	
Power circuit: connector 2 cable(s) 2.516 mm²solid without cable end Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat & Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Safety Reliability Level	le end
Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat @ Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on connector - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	ble end
Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philip Power circuit: 1.7 N.m - on connector - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on connector - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849	ole end
Power circuit: 1.7 N.m - on connector - with screwdriver flat Ø 6 mm Power circuit: 1.7 N.m - on connector - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849-1	lriver flat Ø 6 mm
Power circuit: 1.7 N.m - on connector - with screwdriver Philips No 2 Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Coperating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	
Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver pozid Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849-1	
Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849-1	
Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849-1	
1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849-1	river pozidriv No 2
Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849-1	
B10d = 20000000 cycles contactor with mechanical load conforming to EN 13849-1	
13849-1	to EN/ISO 13849-1
Machanical Durahility 20 Mayeleo	ning to EN/ISO
Mechanical Durability 30 Mcycles	
Maximum Operating Rate 3600 cyc/h 60 °C	

Complementary

Coil Technology	Built-in bidirectional peak limiting diode suppressor
Control Circuit Voltage Limits	0.10.25 Uc (-4060 °C):drop-out DC 0.71.25 Uc (-4060 °C):operational DC
Time Constant	28 ms
Inrush Power In W	5.4 W at 20 °C
Hold-In Power Consumption In W	5.4 W at 20 °C

Auxiliary Contacts Type	type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1 type mirror contact 1 NC conforming to IEC 60947-4-1
Signalling Circuit Frequency	25400 Hz
Minimum Switching Current	5 mA for signalling circuit
Minimum Switching Voltage	17 V for signalling circuit
Non-Overlap Time	1.5 ms on de-energisation between NC and NO contact 1.5 ms on energisation between NC and NO contact
Insulation Resistance	> 10 MOhm for signalling circuit

Environment

Ip Degree Of Protection	IP20 front face conforming to IEC 60529
Climatic Withstand	conforming to IACS E10 conforming to IEC 60947-1 Annex Q category D
Protective Treatment	TH conforming to IEC 60068-2-30
Pollution Degree	3
Ambient Air Temperature For Operation	-4060 °C 6070 °C with derating
Ambient Air Temperature For Storage	-6080 °C
Operating Altitude	03000 m
Fire Resistance	850 °C conforming to IEC 60695-2-1
Flame Retardance	V1 conforming to UL 94
Mechanical Robustness	Vibrations contactor open: 2 Gn, 5300 Hz Vibrations contactor closed: 4 Gn, 5300 Hz Shocks contactor closed: 15 Gn for 11 ms Shocks contactor open: 8 Gn for 11 ms
Height	91 mm
Width	90 mm
Depth	98 mm
Net Weight	0.85 kg

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	9.08 cm
Package 1 Width	9.0 cm
Package 1 Length	9.95 cm
Package 1 Weight	870.0 g

Contractual warranty

Warranty

18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



Transparency RoHS/REACh

Eà

Well-being performance

Reach Free Of Svhc
Toxic Heavy Metal Free
Mercury Free
Rohs Exemption Information Yes
Pvc Free

Certifications & Standards

REACh Declaration
Compliant
EU RoHS Declaration
China RoHS declaration
Pro-active China RoHS declaration (out of China RoHS legal scope)
Product Environmental Profile
The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
End of Life Information
WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to www.P65Warnings.ca.gov