Product data sheet

Specifications



Μ

(!) Discontinued	
Main	
Range	TeSys
Product Name	TeSys LE
Device Short Name	LE1D
Product Or Component Type	Enclosed DOL starter
Device Application	Standard
Utilisation Category	AC-3
Device Composition	Thermal overload relay ordered separately

Discontinued on: Aug 24, 2020

LE1D50AP7A05

Contactor

Push-button reset blue R

TeSys LE - enclosed DOL starter -

50 A - 230 V AC coil - reset

Control Type

Complementary	
Motor Power Kw	15 kW at 220/230 V AC 50/60 Hz 22 kW at 380/400 V AC 50/60 Hz 25 kW at 415 V AC 50/60 Hz 30 kW at 440 V AC 50/60 Hz 30 kW at 500 V AC 50/60 Hz 33 kW at 660/690 V AC 50/60 Hz
[Ith] Conventional Free Air Thermal Current	50 A
[Uc] Control Circuit Voltage	230 V AC 50/60 Hz
Cable Entry Number	1 ISO32 top 3 1 ISO20 + 2 ISO32 bottom
Width	200 mm
Height	300 mm
Depth	158.4 mm
Net Weight	4.85 kg

Environment

Material	Sheet steel
Ip Degree Of Protection	IP65 conforming to IEC 60529
Ik Degree Of Protection	IK09 conforming to IEC 60529
Standards	IEC 60947-4-1
Ambient Air Temperature For Operation	-540 °C

Packing Units

Life Is On Schneider

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1

Sustainability

Green Premium[™] label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

Well-being performance

Reach Free Of Svhc	
Toxic Heavy Metal Free	
Mercury Free	
Rohs Exemption Information	Yes
Eu Rohs Directive	Compliant
	EU RoHS Declaration
China Rohs Regulation	China RoHS declaration
	Pro-active China RoHS declaration (out of China RoHS legal scope)
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins