Specifications



Evx Ferro - con kit - adressable - 10 VA - 6.0 V - 4 Ah

OVA34214E

() Discontinued on: Dec 31, 2015

(!) Discontinued

Main

Range	Evx
Aesthetic Name	Evx Ferro
Product Or Component Type	Conversion kit
Function	Addressable
Wiring Device Additional Information	Can be inhibited with rest mode via Dardo Plus control unit

Complementary

[Ue] Rated Operational Voltage	230 V 50 Hz
Rated Power In Va	10 VA
Connections - Terminals	Screw terminals
Battery Capacity	4 Ah 6 V Ni-Cd (Nickel-Cadmium) in line
Charging Time	24 h

Emergency Luminous Flux	17 % of nominal flux during 1 h 54 W G5 fluorescent FHO T5
	20 % of nominal flux during 1 h 30 38 W GR10q fluorescent GE
	20 % of nominal flux during 1 h 39 W G5 fluorescent FHO T5
	30 % of nominal flux during 1 h 30 24 W G5 fluorescent FHO T5
	40 % of nominal flux during 1 h 30 21 W G5 fluorescent FHE T5
	45 % of nominal flux during 1 h 30 14 W G5 fluorescent FHE T5
	15 % of nominal flux during 1 h 55 W GR10q
	15 % of nominal flux during 1 h 58 W G13
	16 % of nominal flux during 1 h 30 36 W 2G10 18 % of nominal flux during 1 h 30 36 W G13
	18 % of nominal flux during 1 h 30 40 W G10g
	20 % of nominal flux during 1 h 30 32 W G10g
	20 % of nominal flux during 1 h 30 36 W 2G11
	22 % of nominal flux during 1 h 40 W 2GX13
	22 % of nominal flux during 2 h 18 W G13
	25 % of nominal flux during 1 h 2 x 18 W G13
	25 % of nominal flux during 1 h 30 24 W 2G11
	25 % of nominal flux during 2 h 24 W 2G10
	25 % of nominal flux during 2 h 30 22 W G10q
	26 % of nominal flux during 1 h 30 26 W G24q
	26 % of nominal flux during 1 h 40 W 2G11
	28 % of nominal flux during 1 h 30 28 W GR10q
	28 % of nominal flux during 2 h 22 W 2GX13
	28 % of nominal flux during 2 h 30 18 W 2G10
	28 % of nominal flux during 2 h 30 18 W 2G11
	30 % of nominal flux during 1 h 30 26 W Gx24q
	30 % of nominal flux during 1 h 32 W Gx24q
	35 % of nominal flux during 2 h 18 W G24q
	37 % of nominal flux during 2 h 18 W Gx24q
	38 % of nominal flux during 2 h 30 13 W G5
	38 % of nominal flux during 3 h 30 8 W G5
	40 % of nominal flux during 1 h 30 16 W GR10q
	40 % of nominal flux during 3 h 30 10 W G24q
	45 % of nominal flux during 1 h 30 2 x 8 W G5
	45 % of nominal flux during 2 h 13 W G24q
	45 % of nominal flux during 2 h 13 W Gx24q 50 % of nominal flux during 3 h 30 9 W 2G7
	60 % of nominal flux during 3 h 30 7 W 2G7 70 % of nominal flux during 4 h 5 W 2G7
	8 % of nominal flux during 1 h 55 W 2G11
Bulb Type	Indicator LED
Ballast Type	Electromagnetic ballast
Electrical Insulation Class	Class II
Height	Battery: 35 mm
	Circuit: 40 mm
Width	Circuit: 197 mm
Depth	Circuit: 32 mm
	Battery: 39 mm
Distance Between Centers	Circuit: 180 mm
	Battery: 330 mm
Net Weight	0.88 kg
Environment	

Fire Resistance	850 °C	
Standards	IEC 60695-2-10 EN 61347-2-7	

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	4.2 cm
Package 1 Width	8 cm

Package 1 Length	34.5 cm	
Package 1 Weight	0.871 kg	

Contractual warranty

Warranty

18 months