

Miluz - Bossa triple 2-way - assembled (PS) - 10 AX 250 V - white

S3B62230

Main

Range	Miluz
Aesthetic Name	Bossa
Product Or Component Type	Switch

Complementary

Device Presentation	Complete mechanism
Type Of Packing	Flow-pack
Switch Function	Triple 2-way
Local Signalling	Without pilot light
Marking	1-2-L
[In] Rated Current	10 A
[Ue] Rated Operational Voltage	250 V AC
Material	ABS (acrylonitrile butadiene-styrene): wiring device
Number Of Modules	3 modules
Fixing Mode	By screws
Connections - Terminals	Screw-clamp terminals
Cable Cross Section	4 mm²
Awg Gauge	AWG 12
Height	111 mm
Width	73 mm
Depth	36 mm
Embedding Depth	26 mm
Projecting Depth	10 mm

Environment

Standards	ABNT NBR NM 60.669
Product Certifications	NOM/ANCE RETIE

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1

Package 1 Height	4 cm
Package 1 Width	11.5 cm
Package 1 Length	7.7 cm
Package 1 Weight	87 g
Unit Type Of Package 2	CAR
Number Of Units In Package 2	20
Package 2 Height	15.8 cm
Package 2 Width	21.5 cm
Package 2 Length	26.5 cm
Package 2 Weight	1949 g

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >





Transparency RoHS/REACh

Well-being performance

✓ Reach Free Of Svhc
 ✓ Toxic Heavy Metal Free
 ✓ Mercury Free
 ✓ Rohs Exemption Information

Certifications & Standards

Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant EU RoHS Declaration
China Rohs Regulation	China RoHS declaration Pro-active China RoHS declaration (out of China RoHS legal scope)
Environmental Disclosure	Product Environmental Profile
Circularity Profile	No need of specific recycling operations