

# Empty Battery Cabinet, 1100mm wide

GVEBC11

#### **Overview**

Presentation	Empty battery cabinet for use with third party batteries. Battery breaker kit is required (sold separately).
Lead Time	Usually Ships within 2 Weeks

#### Main

Battery Type	VRLA
Provided Equipment	Installation guide

#### **Batteries & Runtime**

Number Of Battery Filled Slots	0
Device Mounting	Enclosed battery cabinet
Battery Power In Vah	0 VAh

#### **Physical**

Height	197 cm	
Width	110 cm	
Depth	85 cm	
Net Weight	230 kg	

#### **Environmental**

Ambient Air Temperature For Operation	040 °C
Ambient Air Temperature For Storage	-2555 °C

## **Packing Units**

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	210 cm
Package 1 Width	97 cm
Package 1 Length	133 cm
Package 1 Weight	250 kg

Excluding VAT and subject to change. Please check with your local distributor through "Where to buy"

#### **Sustainability**

**Eu Rohs Directive** 

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

### Well-being performance

Yes
REACh Declaration

Pro-active China RoHS declaration (out of China RoHS legal scope)

**EU RoHS Declaration** 

Compliant